

Command Set DC10-R

V1.1

COM Settings:	
Baudrate:	9600
Databit:	8
Parity:	None
Stop bit:	1
Handshake:	Off

From Host to DC10-R	Answer
---------------------	--------

Command	Ascii	Action	Ack 1	Ack 2
#U<cr>	35 85 13	Uncap tube and ret. to ready pos. / Tube locked	>	>1
#C<cr>	35 67 13	Cap tube and ret. to ready pos. / Tube released	>	>0
#S<cr>	35 83 13	No action only Status is returned	>1 if in UnCap pos	>0 if in Ready pos

Start:

After power on **DC10-R** is in ready position after 1.5 seconds.

Timeout:

Command:

After command is received **DC10-R** send first Ack ">" after command is complete
DC10-R send second Ack ">0" or ">1".